



# UNITED STATES AIR FORCE RESEARCH LABORATORY

---

## A MATHEMATICAL MODEL OF A GIGAHERTZ TRANSVERSE ELECTROMAGNETIC CELL, I

Sherwood Samn

AIR FORCE RESEARCH LABORATORY  
HUMAN EFFECTIVENESS DIRECTORATE  
DIRECTED ENERGY BIOEFFECTS DIVISION  
2503 Gillingham Drive, Building 175  
Brooks AFB, Texas 78235-5102

Satnam Mathur

USA-MCMR  
McKesson HBOC BioServices  
8308 Hawks Road, Bldg 1168  
Brooks AFB TX 78235-5460

*Approved for public release; distribution unlimited.*

May 1999

DTIC QUALITY INSPECTED 3

19991214 069


## NOTICES

This report is published in the interest of scientific and technical information exchange and does not constitute approval or disapproval of its ideas or findings.

Using Government drawings, specifications, or other data included in this document for any purpose other than Government-related procurement does not in any way obligate the US Government. The fact that the Government formulated or supplied the drawings, specifications, or other data, does not license the holder or any other person or corporation, or convey any rights or permission to manufacture, use, or sell any patented invention that may relate to them.

The Office of Public Affairs has reviewed this report, and it is releasable to the National Technical Information Service, where it will be available to the general public, including foreign nationals.

This report has been reviewed and is approved for publication.



**SHERWOOD SAMN, Ph.D.**  
Project Scientist



**RICHARD L. MILLER, Ph.D.**  
Chief, Directed Energy Bioeffects Division

**DESTRUCTION NOTICE - Destroy by any method that will prevent disclosure of contents or reconstruction of the document.**

# REPORT DOCUMENTATION PAGE

Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden, to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.

1. AGENCY USE ONLY (Leave blank)		2. REPORT DATE May 1999	3. Interim Report- February 1998 -January 1999
4. TITLE AND SUBTITLE A Mathematical Model of a Gigahertz Transverse Electromagnetic Cell, I			5. FUNDING NUMBERS  PE - 62202F PR - 7757 TA - B4 WU - 02
6. AUTHOR(S)  Sherwood Samn Satnam Mathur			
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) USA-MCMR McKesson HBOC Bio-Services 8308 Hawks Road, Bldg 1168 Brooks AFB TX 78235-5460			8. PERFORMING ORGANIZATION REPORT NUMBER
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES) Air Force Research Laboratory Human Effectiveness Directorate Directed Energy Bioeffects Division 2509 Gillingham Drive Bldg 175 Brooks Air Force Base TX 78235-5118			10. SPONSORING/MONITORING AGENCY REPORT NUMBER AFRL-HE-BR-TR 1999-0219
11. SUPPLEMENTARY NOTES Air Force Research Laboratory Technical Monitor: Dr. Sherwood Samn, 210-536-5708			
12a. DISTRIBUTION/AVAILABILITY STATEMENT  Approved for public release; distribution unlimited			12b. DISTRIBUTION CODE
13. ABSTRACT (Maximum 200 words)  A mathematical model for transverse electromagnetic (TEM) cell has been constructed. The model estimates the electric field inside rectangular or flared TEM cells driven by a wideband electromagnetic current pulse. The finite difference time domain (FDTD) approach is used.			
14. SUBJECT TERMS Transverse electromagnetic cell, wideband electromagnetic pulse, finite difference time domain, mathematical model			15. NUMBER OF PAGES 24
			16. PRICE CODE
17. SECURITY CLASSIFICATION OF REPORT UNCLASSIFIED	18. SECURITY CLASSIFICATION OF THIS PAGE UNCLASSIFIED	19. SECURITY CLASSIFICATION OF ABSTRACT UNCLASSIFIED	20. LIMITATION OF ABSTRACT  UL

# Contents

INTRODUCTION	1
THE GTEM CELL	4
A MATHEMATICAL MODEL	4
COMPUTATIONAL RESULTS	7
CONCLUSION	15
BIBLIOGRAPHY	16

# List of Figures

1	An UltraWide-Band (UWB) Exposure Facility and Data Acquisition System.	2
2	Dimensions of the GTEM Cell. . . . .	3
3	Excitation Plane $\Omega$ . (Not to scale) . . . . .	4
4	NBC Cell. . . . .	7
5	Potential (V) in Excitation Plane. . . . .	8
6	Calculated and Measured Relative E Field for 100 MHz Sinusoidal Input. . .	8
7	Calculated and Measured Relative E Field for 500 MHz Sinusoidal Input. . .	9
8	Calculated and Measured Relative E Field for 1 GHz Sinusoidal Input. . .	9
9	Calculated E Field in Excitation Plane for $V=42.75$ kV. . . . .	10
10	Selected Cross Sections of the GTEM cell. . . . .	11
11	Simulated Input Voltage Source. . . . .	13
12	Calculated $E_y$ at 4 points in CS BB vs Measured $E_y$ . . . . .	13
13	Contour Plot of Measured Peak E. . . . .	14
14	Contour Plot of Calculated Peak E. . . . .	14

# A Mathematical Model of a Gigahertz Transverse Electromagnetic Cell, I.

## INTRODUCTION

The Gigahertz Transverse Electromagnetic Cell (GTEM) has become a popular tool in the electromagnetic compatibility community for testing radiated emission and immunity (susceptibility) work [5, 6, 13, 19]. Recently it has found use in the electromagnetic dosimetry community [8]. Whatever the application, it is important to know exactly what the field characteristics are inside the cell, both before and after a test object is placed in it. The field characteristics in an empty cell can be obtained by direct measurement. However, once an object is placed in the cell, the field is disturbed and it is no longer easy to know or even measure the field experienced by the object [14, 15, 16]. Mathematical modeling hence becomes indispensable. Using measurements from an empty cell, one can validate a mathematical model of the cell. Knowing the electrical properties of the object being tested, one can then estimate the field experienced by the test object using the model. Moreover, the scattered field from the object, if measured, can also be used to further validate the mathematical model.

Mathematical analysis of various aspects of GTEM cells can either be theoretical [11, 17, 18, 21, 22, 23, 28, 29, 31, 32] or computational (modeling) [9, 12, 16, 25]. Here we describe our initial efforts to model a 1.92m-long GTEM cell (Sandia National Laboratories, Albuquerque, New Mexico) using a finite difference time domain method. The GTEM cell modeled is part of an ultrawide-band (UWB) exposure system currently in use at U.S. Army-Medical Research and Materiel Command (USA-MCMR) to study the bioeffects of RF radiation in experimental animals. A precise knowledge of the electric field inside the test subject is required to calculate the energy absorption rate in the animal.





Figure 1: An Ultrawide-Band (UWB) Exposure Facility and Acquisition System

**All Dimensions are in mm**





## THE GTEM CELL

A detail description of the GTEM cell and related electronics and issues can be found in the references [1, 24]. A schematic of the UWB exposure facility and acquisition system is shown in Figure 1 and the dimensions of the GTEM Cell (in a vertical cross section) are shown in Figure 2.

## A MATHEMATICAL MODEL

To calculate the electromagnetic field inside the GTEM cell, we use a finite difference time domain (FDTD) code modified from Kunz and Luebbers [20]. This is basically the Yee's algorithm [30] enhanced with more recent treatment of absorbing boundary conditions [3, 4].

### A. Source

Instead of modeling the complete GTEM cell starting from the source (a spark-gap pulse generator) outside the main chamber, we assumed that the field inside the cell is driven by an equivalent source that is spread over an excitation plane (more precisely, a square annulus) located near the entrance to the cell. In particular, if the base plane (cross section AA' in Figure 2) of the cell is located at  $z = 0$ , then the excitation plane is assumed to be located at  $z = z_e$  where  $z_e$  has a magnitude equivalent to the thickness of a few Yee's cells. The excitation plane, a region  $\Omega$  in the cross section of the GTEM cell at  $z = z_e$ , is depicted in Figure 3.




Figure 3: Excitation Plane  $\Omega$ . (Not to scale)

Assume, at a given time  $t$ , the inner rectangle, which corresponds to the septum of the GTEM cell, has a uniform voltage  $V_{\text{spt}}(t)$  and the outer rectangle, which corresponds to the conductive walls of the cell, is grounded, then the electric field  $\mathbf{E}^{\text{ex}}(x, y, z_e, t)$  in  $\Omega$  induced by  $V_{\text{spt}}(t)$  can be calculated by

$$\mathbf{E}^{\text{ex}}(x, y, z_e, t) = -\nabla\phi(x, y, t)$$

where the potential  $\phi$  is the unique solution of the 2-dimensional Laplace's Equation

$$\nabla^2\phi = 0 \quad \text{in } \Omega \quad (1)$$

subject to the boundary condition

$$\phi(x, y, t) = \begin{cases} V_{\text{spt}}(t) & \text{for } (x, y) \in \text{inner rectangle} \\ 0 & \text{for } (x, y) \in \text{outer rectangle} \end{cases}$$

It can easily be verified that if

$$V_{\text{spt}}(t) = V_m \cdot \Psi(t)$$

where  $V_m$  is a constant and  $\Psi(t)$  is an arbitrary function of  $t$  and if  $\phi_m(x, y)$  is the unique solution to Equation (1) subject to the boundary condition

$$\phi_m(x, y) = \begin{cases} V_m & \text{for } (x, y) \in \text{inner rectangle} \\ 0 & \text{for } (x, y) \in \text{outer rectangle} \end{cases}$$

then

$$\begin{aligned} \phi(x, y, t) &= \phi_m(x, y) \cdot \Psi(t) \\ \mathbf{E}^{\text{ex}}(x, y, z_e, t) &= -\nabla\phi(x, y, t) \\ &= -\Psi(t) \nabla\phi_m(x, y) \\ &= \Psi(t) \mathbf{E}_m^{\text{ex}}(x, y) \end{aligned}$$

where

$$\mathbf{E}_m^{\text{ex}}(x, y) := -\nabla\phi_m(x, y)$$

This implies that we only have to solve Equation (1) once for  $\phi_m(x, y)$  to determine the excitation field  $\mathbf{E}^{\text{ex}}(x, y, z_e, t)$  for all time  $t$ . Some additional discussion on the implementation of excitation sources in FDTD can be found in [2, 7].

## B. Boundary Conditions

The GTEM cell is terminated by an anechoic wall consisting of a series of resistive low frequency terminators and pyramidal microwave absorbers for the high frequency end of the frequency spectrum. These are constructed to minimize reflections at the terminal end that could compromise the field at a test site within the cell. We model this by placing a Berenger's perfectly matched layer (PML) [3, 4] at this terminal end to simulate non-reflection of electromagnetic waves. We also place a PML at the base plane (cross section AA' in Figure 2) to absorb fictitious backward waves generated by the assumed excitation plane. The four other walls of the GTEM cell are modeled faithfully as perfectly electrically conducting (PEC) boundary.

## C. Staircase Errors

The GTEM cell is flared. The side walls cannot all be aligned with the rectangular grid axes in FDTD. It is well known that this leads to so-called staircase errors in the computations. For the work reported here, we took the simple, albeit inefficient, approach of using smaller mesh sizes to minimize these errors. More sophisticated methods such as locally conforming FDTD schemes [26] will be used in the future.

## RESULTS

We have tested our computational method on several different TEM cells using a variety of input sources. The results have been excellent on simple cases and reasonable on more complex ones. We will report on two cases below.

### I. A Non-flared Square cell

In this computational experiment, we use the square TEM cell (the "NBS cell") studied first experimentally by Crawford [10] and latter theoretically (quasi-statically) by Spiegel [27]. This square cell has dimensions shown in Figure 4.




Figure 4: NBC Cell.

Unlike Spiegel's theoretical cell, the cell we studied has a finite non-zero thickness that is one FDTD cell thick. The FDTD cell we used is 5 mm thick. The input for this computational experiment is sinusoidal. Three frequencies were chosen: 100 MHz, 500 MHz, and 1 GHz. The cutoff frequency for the first order TE mode ( $TE_{10}$ ) for this cell is slightly above 500 MHz [10].

We picked a the TEM cell that is 100 cm long (in the  $z$ -direction) and monitored the electric field at approximately the same locations where measurements were made by Crawford [10] and also by Spiegel, et al [27]. The cross section in which these points are taken is halfway ( $z = 50$  cm) along the TEM cell. The results are shown in Figures 4 through 7. Figure 5 shows the potential field in the cross section at  $z = 2.5$  cm. Figures 6 through 8 are the relative time-averaged magnitude of the electric field when using the frequencies 100 MHz, 500 MHz, and 1 GHz respectively. Also shown are the measured values. There is general agreement between the measured and the calculated. As expected, the first two calculated fields are practically identical, as they are both below cutoff.




Figure 5: Potential (V) in Excitation Plane.




Figure 6: Calculated and Measured Relative E Field for 100 MHz Sinusoidal Input.




Figure 7: Calculated and Measured Relative E Field for 500 MHz Sinusoidal Input.




Figure 8: Calculated and Measured Relative E Field for 1 GHz Sinusoidal Input.

## II. A flared cell driven by a wide-band pulse

The GTEM cell shown in Figure 1 has dimensions shown in Figure 2 and Figure 10. The UWB pulse applied to the GTEM cell can be approximated by

$$V(t) = V_m \cdot \Psi(t)$$

where

$$\begin{aligned} V_m &= 130 \text{ kV} \\ \Psi(t) &= e^{-\alpha t} - e^{-\beta t} \\ \alpha &= 1.19661\text{E} + 9 \text{ s}^{-1} \\ \beta &= 1.99573\text{E} + 10 \text{ s}^{-1} \end{aligned}$$

This pulse has a rise time of 150 ps and a pulse width of 1 ns. This is depicted in Figure 11.

Setting  $V_{\text{spt}}(t) = V_m$  and solving the Laplace's equation in Equation (1) yields the solution  $\phi_m(x, y)$  similar in shape to that shown in Figure 5. The corresponding vector field  $\mathbf{E}_m^{\text{ex}}(x, y)$  is shown in Figure 9.






Figure 9: Calculated E Field in Excitation Plane for  $V=42.75 \text{ kV}$ .


Section on A-A'



Section on C-C'



Section on B-B'



All dimensions are in mm

Figure 10: GTEM Cell Cross sections



Using this pulse, we calculated the field inside the cell using FDTD. The main parameters used are:

$$\text{space discretization: } \Delta x = 0.005 \text{ m}$$

$$\text{space discretization: } \Delta y = 0.005 \text{ m}$$

$$\text{space discretization: } \Delta z = 0.005 \text{ m}$$

$$\text{time step: } \Delta t = 9.629 \times 10^{-12} \text{ sec}$$

These values are dictated by the high frequency content of the pulse and the stability requirement of the method [20].

In our simulation, we calculated the  $\mathbf{E}$  field at several points in the proximity of the location where the actual measurements had previously been taken. These selected points are in the center of cross section BB' (Figure 2) near the bottom of the cell. Figure 12 compares the calculated  $E_y$  at the selected points to the measured  $E_y$ . The amplitude  $V_m$  of the voltage source at the excitation plane was picked (trial and error) to be 42.75 kV in this particular calculation.

We have also measured and calculated several indices related to the  $\mathbf{E}$  field at each point in a grid (not shown here) on the bottom wall ("parallel" to the septum). Among these indices is the peak intensity of the  $\mathbf{E}$  field. From this a contour plot is made. This is shown in Figure 13. We used the model to calculate the peak  $\mathbf{E}$  field intensity at approximately the same points and constructed the corresponding contour plot. This is shown in Figure 14. The two contour plots, Figure 13 and Figure 14 are qualitatively similar. (At this time, we have not fine tuned the choice of the amplitude  $V_m$  of the voltage source at the excitation plane to make the comparison better.)




Figure 11: Simulated Input Voltage Source.




Figure 12: Calculated  $E_y$  at 4 points in CS BB vs Measured  $E_y$ .




Figure 13: Contour Plot of Measured Peak E.




Figure 14: Contour Plot of Calculated Peak E.

## CONCLUSION

In this report we have described a general mathematical model that can be used to estimate the electric field in a large class of TEM cells. An excitation plane was used to simulate the input to the GTEM cell and the popular FDTD method was then used to calculate the field anywhere and anytime inside the cell. To our knowledge this is the first documented use of FDTD to model an ultrawide-band exposure system. We tested our model on the simple (square) NBC cell and on a flared GTEM cell. The results have been reasonable in all cases. We believe this effort has laid the foundation for further fruitful research. Future improvements to the model include implementing methods to reduce staircase errors and to allow for multiple grids. These improvements are necessary for the efficient and accurate modeling of relatively small objects placed in the cell. When accomplished, they will have increased the scope and capability of electromagnetic compatibility and dosimetry research.

# Bibliography

- [1] J. Z. Bao, J.C. Lee, M. E. Belt, D. D. Cox, S. P. Mathur, and S. T. Lu, *Error Correction in Transient Electromagnetic Field Measurements Using Deconvolution Techniques*, Ultra-Wideband, Short-Pulse Electromagnetics, vol. 3, pp. 373-380, 1997.
- [2] G. Bellanca, *High-Accuracy Assigned Power Excitation for the FDTD Technique*, IEEE Microwave and Guided Wave Letters, vol. 7, pp. 411-413, 1997.
- [3] J. P. Berenger, *A Perfectly Matched Layer for the Absorption of Electromagnetic Waves*, J. Comput. Physics, vol 114, pp. 185-200, 1994.
- [4] J. P. Berenger, *Three-Dimensional Perfectly Matched Layer for the Absorption of Electromagnetic Waves*, J. Comput. Physics, vol 127, pp. 363-379, 1996.
- [5] E. L. Bronaugh, *Simplifying EMI immunity (susceptibility) tests in TEM cells*, Symp. Record IEEE 1990 International Symp. Electromagn. Compat., Aug. 21-23, Washington, pp. 488-491, 1990.
- [6] J. T. Brown, *Using TEM cells for shielding performance evaluation*, Symp. Record IEEE 1990 International Symp. Electromagn. Compat., Aug. 21-23, Washington, pp. 495-499, 1990.
- [7] D. N. Buechler, D. H. Roper, C. H. Durney, and D. A. Christensen, *Modeling Sources in the FDTD Formulation and Their Use in Quantifying Source and Boundary Condition Errors*, IEEE Trans. Microwave Theory and Tech., vol 43, pp. 810-814, 1995.
- [8] M. Burkhardt, K. Pokovic, M. Gnos, T. Schmid, and N. Kuster, *Numerical and Experimental Dosimetry of Petri Dish Exposure Setups*, Bioelectromagnetics, vol 17, pp. 483-493, 1996.
- [9] J. H. Collins and P. Daly, *Calculations for Guided Electromagnetic Waves using Finite-Difference Methods*, J. Electronics and Control, vol. 14, pp. 361-380, 1963.
- [10] M. L. Crawford, *Generation of Standard EM Fields Using TEM Transmission Cells*, IEEE Trans. Electromag. Compat., vol. 16, No. 4, pp. 189-195, Nov, 1974.

- [11] O. R. Cruzan and R. V. Garver, *Characteristic Impedance of Rectangular Coaxial transmission lines*, IEEE Trans. Microwave Theory Tech., vol. MTT-12, pp. 488-495, 1964.
- [12] S. K. Das and B. K. Sinha *Numerical Solution of Higher Order Mode Cut-Off Frequencies in Symmetric TEM Cells Using Finite Element Method*, IEEE Trans. Electromagn. Compat., vol 32, pp. 264-268, 1990.
- [13] D. Hansen, P. Wilson, D. Koenigstein, and H. Schaer, *A broadband alternative EMC test chamber based on a TEM cell anechoic-chamber hybrid concept*, in Int. Symp. Electromagn. Compat., Nagoya, Japan, Sept. 1989
- [14] D. Hansen, D. Ristau, T. Spaeth, W. A. Radasky, and Kenneth S. Smith, *Expansions on the GTEM Field Structure Problem*, Proceedings of the IEEE Electromagnetic Compatibility Sym. 1995, Atlanta, pp. 538-542, Aug. 1995.
- [15] D. Hansen, D. Ristau, W. A. Radasky, and K. S. Smith, *Sources of Problems in the GTEM Field Structure and Recommended Solutions*, Proceedings of the IEEE Electromagnetic Compatibility Sym. 1996, Santa Clara, pp. 48-51, Aug. 1996.
- [16] J. Van Hese, L. Martens, D. De Zutter, C. De Wagter, L. O. G. Malmgren, B. R. R. Person, and L.G. Salford, *Simulation of the Effect of Inhomogeneities in TEM Transmission Cells using the FDTD-Method*, IEEE Trans. Electromagn. Compat., vol 34, pp. 292-298, 1992.
- [17] K. Huang and W. Lin, *Calculation of Characteristic Impedance of Broadband TEM Cell (BTEM Cell)*, Microwave and Optical Technology Letters, vol. 4, No. 12, pp. 555-557, Nov. 1991.
- [18] K. Huang and Y. Liu, *A Simple Method for Calculating Electric and Magnetic Fields in GTEM Cell*, IEEE Trans. Electromagn. Compat., vol. 36, No. 4, pp. 355-358, Nov. 1994.
- [19] D. Koenigstein and D. Hansen, *A new family of TEM-cells with enlarged bandwidth and optimized working volume*, in 7th Symp. Electromag. Compat., Zurich, Mar. pp. 127-132, 1987.
- [20] K. Kunz and R. Luebbers, *The Finite Difference Time Domain Method for Electromagnetics*, CRC Press, 1993.
- [21] R. Lampe, P. Klock, D. Tanner, and P. Mayes, *Analysis and Experiment Concerning the Cutoff Frequencies of Rectangular Striplines*, IEEE Trans. Microwave Theory Tech., vol. MTT-34, No. 8, pp. 898-899, Aug. 1986.
- [22] R. De Leo, T. Rozzi, C. Svara, and L. Zappelli, *Rigorous Analysis of the GTEM Cell*, IEEE Trans. Microwave Theory Tech., vol. MTT-39, No. 3, pp. 488-500, Mar. 1991.

- [23] R. De Leo, L. Pierantoni, T. Rozzi, and L. Zappelli, *Dipole Excitation and Scattering by Spherical Objects in GTEM Cell*, IEEE Trans. Microwave Theory Tech., vol. 42, No. 9, pp. 1700-1708, Sep. 1994.
- [24] Shin-Tsu Lu, Satnam, P. Mathur, Yahya Akyel, and Jonathan Lee, *Ultrawide-Band Electromagnetic Pulses Induced Hypotension in Rats*, Physiology and Behavior, vol. 65, Nos. 4/5, pp. 753-761, 1999.
- [25] William A. Radasky, Kenneth S. Smith, Diethard Hansen and Detlef Ristau, *Calculations and Measurements of Fast EM Pulses in the GTEM Cell*, Proceedings of the IEEE Electromagnetic Compatibility Sym. 1996, Santa Clara, pp. 52-57, Aug. 1996.
- [26] C. J. Railton and J.B. Schneider, *An Analytical and Numerical Analysis of Several Locally Conformal FDTD Schemes*, IEEE Trans. Microwave Theory and Techniques, vol. 47, no. 1, pp. 56-66, 1999.
- [27] R. J. Spiegel, W. T. Joines, C. F. Blackman, and A. W. Wood, *A Method for Calculating Electric and Magnetic Fields in TEM Cells at ELF*, IEEE Trans. Electromagnetic Compatibility, Vol. EMC-29, No. 4, Nov 1987.
- [28] C. Wan, *Conformal Mapping Analysis of a Modified TEM Cell*, IEEE Trans. Electromagn. compat., vol 35, pp. 109-113, 1993.
- [29] P. F. Wilson and M. T. Ma, *Simple Approximation Expressions for Higher Order Mode Cutoff and Resonant Frequencies in TEM Cells*, IEEE Trans. Electromag. Compat., vol. 28, No. 3, pp. 125-130, Aug, 1986.
- [30] K. S. Yee, *Numerical solution of initial boundary value problems involving Maxwell's equations in isotropic media*, IEEE Trans. Antennas and Propagation, vol. 14, pp. 302-307, 1966.
- [31] J. Zhang and J. M. Fu, *Higher Order Mode Cutoff Frequencies in TEM Cells Calculated with TLM Method*, IEEE Trans. Electromag. Compat., vol. 30, No. 4, pp. 563-567, Nov, 1988.
- [32] J. Zhang *A Note on the Cutoff Frequency of  $TE_{01}$  Mode in TEM Cells*, IEEE Trans. Electromag. Compat., vol. 33, No. 2, pp. 145-146, May, 1991.